arXiv:math/0501368v1 [math.OA] 24 Jan 2005

OPERATOR-VALUED MOMENT SERIES OF THE GENERATING OPERATOR OF $L(F_2)$ OVER THE COMMUTATOR GROUP VON NEUMANN ALGEBRA $L(K)$

ILWOO CHO

Abstract. In this paper, we will consider the generating operator $x = a + b + a^{-1} + b^{-1}$ of the free group factor $L(F_2)$, where $F_2 = < a, b >$ is the free group with two generators a and b. Let $K = < h >$ be the commutator group of a and b with one generator $h = aba^{-1}b^{-1}$. Then we can construct the group von Neumann algebra $L(K)$ and the conditional expectation E : $L(F_2) \rightarrow L(K)$, defined by $E\left(\sum_{g\in F_2} \alpha_g g\right) = \sum_{k\in K} \alpha_k k$, for all $\sum_{g\in F_2} \alpha_g g$ in $L(F_2)$. Then $(L(F_2), E)$ is the W^*-probability space with amalgamation over $L(K)$. In this paper, we will compute the **trivial** operator-valued moment series of the generating operator $a+b+a^{-1}+b^{-1}$ of $L(F_2)$, over $L(K)$. This computation is the good example for studying the operator-valued distribution, since the operator-valued moment series of operator-valued random variables contain algebraic and combinatorial free probability information about the opeartor-valued distributions.

From mid 1980's, Free Probability Theory has been developed. Here, the classical concept of Independence in Probability theory is replaced by a noncommutative analogue called Freeness (See [9]). There are two approaches to study Free Probability Theory. One of them is the original analytic approach of Voiculescu and the other one is the combinatorial approach of Speicher and Nica (See [1], [2] and [3]). Speicher defined the free cumulants which are the main objects in Combinatorial

approach of Free Probability Theory. The free cumulants of random variables are gotten from the free moments of random variables via the Möbius inversion (or vice versa). But in this paper, we will concentrate only on computing the free moments of certain random variables (See [3]). Also, Speicher considered the operator-valued free probability theory, which is also defined and observed originally by Voiculescu (See [9]). In this paper, we will observe the important example of such operator-valued free probability.

Let F_N be a free group with N-generators and let $L(F_N)$ be the free group factor defined by

$$L(F_N) = \overline{\mathbb{C}[F_N]}^w.$$

Key words and phrases. Free Group Factors, Moment Series with Amalgamation, Generating Operators or Radial Operators, The Recurrence Diagram for $N \in \mathbb{N}$..

In this paper, by using so-called the recurrence diagram found in [13] and [14], we will compute the **trivial** operator-valued moment series of the genarating operator G of the free group factor $L(F_2)$, defined by

$$G = a + b + a^{-1} + b^{-1} \in L(F_2),$$

over the group von Neumann algebra $L(K)$, where $F_2 = < a, b >$ and $K = < aba^{-1}b^{-1} >$ is the commutator group of a and b in F_2. i.e,

$$L(K) \overset{def}{=} \overline{\mathbb{C}[< aba^{-1}b^{-1} >]}^{w}.$$

Throughout this paper, we will fix a and b as the generators of the free group F_2 and we will also fix $h = aba^{-1}b^{-1}$ as the generator of the group K which is group isomorphic to the integers $\mathbb{Z}$. Notice that the commutator group K is a subgroup of F_2 and hence the group von Neumann algebra $L(K)$ is a W^*-subalgebra of the free group factor $L(F_2)$. Let x be an operator in $L(F_2)$. Then there exists the Fourier expansion of x,

$$x = \sum_{g \in F_2} \alpha_g u_g, \text{ with } \alpha_g \in \mathbb{C}, \text{ for all } g \in F_2.$$

We can regard all $g \in F_2$ as unitaries u_g in $L(F_2)$. For the convenience, we will denote these unitaries u_g just by g. With this notation, it is easy to check that

$$g^* = u_g^* = u_g^{-1} = u_{g^{-1}} = g^{-1} \text{ in } L(F_2),$$

where g^{-1} is the group inverse of g in F_2. We can define the conditional expectation $E : L(F_2) \to L(K)$ by

$$E\left(\sum_{g \in F_2} \alpha_g g\right) = \sum_{k \in K} \alpha_k k.$$

Then we have the W^*-probability space $(L(F_2), E)$ with amalgamation over $L(K)$. Let G be the generating operator, which is also said to be the radial operator of F_2, $a + b + a^{-1} + b^{-1}$ in $L(F_2)$.

Now, let $B \subset A$ be von Neumann algebras and assume that there is a conditional expectation $F : A \to B$. Then the algebraic pair (A, F) is called the W^*-probability space with amalgamation over B (in short, the W^*-probability space over B). We say that each element a of (A, F) is a B-valued (or operator-valued) random variable. Voiculescu defined the n-th B-valued (or operator-valued) moment of the B-valued random variable a by

$$F(b_1 a \ldots b_n a), \text{ for all } n \in \mathbb{N},$$

where $b_1, ..., b_n \in B$ are arbitrary. (Recall that, in [1], Speicher defined the n-th moment of $a \in (A, F)$ by $F\left(ab_2a...b_na\right)$, for arbitrary $b_2, ..., b_n \in B$) Different from the scalar-valued case when $B = \mathbb{C}$, since B and A are not cummutative, in general, we have to consider the case when $b_1, ..., b_n$ are not $1_B = 1_A$. When $b_1 = ... = b_n = 1_B$, we say that the n-th B-valued moment of a is the trivial n-th B-valued moment of a. However, if B and A are commutative (in other words, if $B = C_A(B)$), then the trivial moment $F(a^n)$ contains the full free probability data for the B-valued moments, since

$$F(b_1a...b_na) = (b_1 \cdots b_n)\, F(a^n), \text{ for all } n \in \mathbb{N}.$$

Remark that, in our case, $L(K)$ and $L(F_2)$ are not commutative, because, for instance,

$$ah = a^2ba^{-1}b^{-1} \neq aba^{-1}b^{-1}a = ha.$$

In this paper, we will concentrate on computing the trivial $L(K)$-valued moments of the generating operator $G = a + b + a^{-1} + b^{-1}$ of $L(F_2)$. As we mentioned in the previous paragraph, since $L(K)$ and $L(F_2)$ are not commutative, these trivial operator-valued moments of G do not contain the complete free probability data of G. But the computation, itself, provides the way how to compute the operator-valued moments of G.

It is easy to see that the first, second and third trivial $L(K)$-moments of G vanish. i.e,

$$E\left(G^k\right) = 0_{L(K)}, \text{ for } k = 1, 2, 3,$$

since G^k does not contain the h^n-term, for $k = 1, 2, 3$ and for $n \in \mathbb{Z}$, where $h = aba^{-1}b^{-1}$ and $h^{-1} = bab^{-1}a^{-1}$. However, fourth trivial $L(K)$-moment $E(G^4)$ of G contains the h-term and the h^{-1}-term. So, finding the trivial $L(K)$-moments of G is to find the h^k-terms of G^n, for all $k \in \mathbb{Z}$ and $n \in \mathbb{N}$.

The following recurrence diagram will play a key role to find such trivial operator-valued moment series of the generating operator G of $L(F_2)$;

$$\begin{tikzcd}
 & & & & & p_0^2 \arrow[d] & = 2N \\
 & & & & & q_1^3 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr, shift left] \arrow[dr, shift right] & = (2N-1) + 2N \\
 & & & & p_2^4 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr] & & p_0^4 \arrow[dl] \\
 & & & q_3^5 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr] & & q_1^5 \arrow[dl] \arrow[dr, shift left] \arrow[dr, shift right] & \\
 & & p_4^6 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr] & & p_2^6 \arrow[dl] \arrow[dr] & & p_0^6 \arrow[dl] \\
 & q_5^7 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr] & & q_3^7 \arrow[dl] \arrow[dr] & & q_1^7 \arrow[dl] \arrow[dr, shift left] \arrow[dr, shift right] & \\
p_6^8 & & p_4^8 & & p_2^8 & & p_0^8 \\
\vdots & & \vdots & & \vdots & & \vdots
\end{tikzcd}$$

where

$$\begin{array}{rl}
\swarrow\swarrow & : \ (2N-1) + [\text{former term}] \\
\searrow & : \ (2N-1) \cdot [\text{former term}] \\
\swarrow & : \ \cdot + [\text{former term}]
\end{array}$$

and

$$\searrow\searrow \ : \ (2N) \cdot [\text{former term}].$$

In this paper, we obtain good applications about the above recurrence diagram. We will re-compute the moment series of the generating operators of the free group factor $L(F_N)$, for all $N \in \mathbb{N}$, by using the above recurrence diagram. This would be the one application of this recurrence diagram (See Chapter 1). When $N = 2$, we can apply this recurrence diagram to compute the trivial operator-valued moment series of the generating operator of $L(F_2)$ (See Chapter 2). Remark that to study (scalar-valued or operator-valued) moment series of elements in an operator algebra is to study (scalar-valued or operator-valued) free distributions of elements in that operator algebra. So, the computations in this paper about generating operators contain the free probability information about free distribution of those generating operators. And the free probability information is determined by the above recurrence diagram.

In Chapter 1, we will re-compute the (scalar-valued) moment series of the generating operator of $L(F_N)$, by using the recurence diagram found in [13] and [14]. The moment series of the generating operator of $L(F_N)$ is already known, but here we will compute it again, by using the above recurrence diagram. In Chapter 2, by using the reccurence diagram when $N = 2$, we will compute the trivial operator-valued moment series of the generating operator $G = a + b + a^{-1} + b^{-1}$ of $L(F_2)$. Remark that the moment series in Chapter 1 is a scalar-valued moment series and the trivial operator-valued moment series in Chapter 2 is a operator-valued (operator-valued) moment series.

1. Moment Series of the Generating Operator of $L(F_N)$

Let A be a von Neumann algebra and let $\tau : A \to \mathbb{C}$ be the normalized faithful trace. Then we call the algebraic pair (A, τ), the W^*-probability space and we call elements in (A, τ), random variables. Define the collection Θ_s, consists of all formal series without the constant terms in noncommutative indeterminants $z_1, ..., z_s$ $(s \in \mathbb{N})$. Then we can regard the moment series of random variables as elements of Θ_s.

Definition 1.1. *Let (A, τ) be a W^*-probability space with its normalized faithful trace τ and let $a \in (A, \tau)$ be a random variale. The moment series of a is defined by the formal series in Θ_1,*

$$M_a(z) = \textstyle\sum_{n=1}^{\infty} \tau(a^n)\, z^n \ .$$

The coefficients $\tau(a^n)$ are called the n-th moments of a, for all $n \in \mathbb{N}$.

Let H be a group and let $L(H)$ be a group von Neumann algebra. i.e,

$$L(H) = \overline{\mathbb{C}[H]}^{w}.$$

Precisely, we can regard $L(H)$ as a weak-closure of the group algebra generated by H and hence

$$L(H) = \overline{\{ \sum_{g \in H} t_g g : g \in H\}}^{w}.$$

It is well known that $L(H)$ is a factor if and only if the given group H is icc. (Since the free group F_N with N-generators is icc, the von Neumann group algebra $L(F_N)$ is a factor and it is called the free group factor.)

Now, define the canonical trace $\tau : L(H) \to \mathbb{C}$ by

$$\tau\left(\sum_{g \in H} t_g g \right) = t_{e_H}, \ \text{ for all } \ \sum_{g \in H} t_g g \in L(H),$$

where e_H is the identity of the group H. It is easy to check that the trace τ is normalized and faithful. So, the algebraic pair $(L(H), \tau)$ is a W^*-pobability space. Assume that the group H has its generators $\{g_j : j \in I\}$. We say that the operator

$$G = \sum_{j \in I} g_j + \sum_{j \in I} g_j^{-1},$$

the generating operator of $L(H)$. For instance, if we have a free group $F_N = < g_1, ..., g_N >$, then the generating operator of the free group factor $L(F_N)$ is

$$g_1 + ... + g_N + g_1^{-1} + ... + g_N^{-1}.$$

Rest of this chapter, we will consider the moment series of the generating operator G of $L(F_N)$.

From now, fix $n \in \mathbb{N}$. And we will denote free group factor $L(F_N)$ by A. i.e

$$A = \overline{\{ \sum_{g \in F_N} t_g g : t_g \in \mathbb{C}\}}^{w}.$$

Recall that there is the canonical trace $\tau : A \rightarrow \mathbb{C}$ defined by

$$\tau \left(\sum_{g \in F_N} t_g g \right) = t_e,$$

where $e \in F_N$ is the identity of F_N and hence $e \in L(F_N)$ is the unity $1_{L(F_N)}$. The algebraic pair $(L(F_N), \tau)$ is a W^*-probability space. Let G be the generating operator of $L(F_N)$. i.e

$$G = g_1 + ... + g_N + g_1^{-1} + ... + g_N^{-1},$$

where $F_N = < g_1, ..., g_N >$. It is well-known that if we denote the sum of all words with length n in $\{g_1 , g_1^{-1} , ..., g_N, g_N^{-1}\}$ by

$$X_n = \sum_{|w|=n} w \in A, \text{ for all } n \in \mathbb{N},$$

then the following two recurrence relations (1.1) and (1.2) hold true, whenever $N \geq 2$;

$$X_1 X_1 = X_2 + 2N \cdot e \qquad (n = 1) \tag{1.1}$$

and

$$X_1 X_n = X_{n+1} + (2N-1) X_{n-1} \qquad (n \geq 2) \tag{1.2}$$

(See [15]). In our case, we can regard our generating operator G as X_1 in A, by the very definition of G.

By using the relation (1.1) and (1.2), we can express G^n in terms of X_k's ; For example, $G = X_1$,

$$G^2 = X_1X_1 = X_2 + 2N \cdot e,$$

$$\begin{aligned} G^3 &= X_1 \cdot X_1^2 = X_1\left(X_2 + (2N)e\right) = X_1X_2 + (2N)X_1 \\ &= X_3 + (2N-1)X_1 + (2N)X_1 = X_3 + \left((2N-1) + 2N\right)X_1, \end{aligned}$$

$$G^4 = X_4 + \left((2N-1) + (2N-1) + 2N\right)X_2 + (2N)\left((2N-1) + (2N)\right)e,$$

$$\begin{aligned} G^5 = {} & X_5 + \left((2N-1) + (2N-1) + (2N-1) + 2N\right)X_3 \\ & + \left((2N-1)\left((2N-1) + (2N-1) + (2N)\right) + (2N)\left((2N-1) + (2N)\right)\right)X_1, \end{aligned}$$

$$\begin{aligned} G^6 = {} & X_6 + \left((2N-1) + (2N-1) + (2N-1) + (2N-1) + 2N\right)X_4 \\ & +\{(2N-1)\left((2N-1) + (2N-1) + (2N-1) + (2N)\right) \\ & \qquad +(2N-1)\left((2N-1) + (2N-1) + (2N)\right) \\ & \qquad\qquad +(2N-1)((2N-1) + (2N))\}X_2 \\ & +(2N)\left((2N-1)\left((2N-1) + (2N-1) + (2N)\right)\right) + (2N)((2N-1) + (2N)))\,e, \end{aligned}$$

etc.

So, we can find a recurrence relation to get G^n $(n \in \mathbb{N})$ with respect to X_k's $(k \leq n)$. Inductively, G^{2k-1} and G^{2k} have their representations in terms of X_j's as follows ;

$$G^{2k-1} = X_1^{2k-1} = X_{2k-1} + q_{2k-3}^{2k-1}X_{2k-3} + q_{2k-5}^{2k-1}X_{2k-5} + ... + q_3^{2k-1}X_3 + q_1^{2k-1}X_1$$

and

$$G^{2k} = X_1^{2k} = X_{2k} + p_{2k-2}^{2k}X_{2k-2} + p_{2k-4}^{2k}X_{2k-4} + ... + p_2^{2k}X_2 + p_0^{2k}e,$$

where $k \geq 2$. Also, we have the following recurrence relation, by the straightforward computation ;

Proposition 1.1. *Let's fix $k \in \mathbb{N} \setminus \{1\}$. Let q_i^{2k-1} and p_j^{2k} $(i = 1, 3, 5, ..., 2k-1, ...$ and $j = 0, 2, 4, ..., 2k, ...)$ be given as before. If $p_0^2 = 2N$ and $q_1^3 = (2N-1) + (2N)^2$, then we have the following recurrence relations ;*

(1) Let

$$G^{2k-1} = X_{2k-1} + q_{2k-3}^{2k-1}X_{2k-3} + ... + q_3^{2k-1}X_3 + q_1^{2k-1}X_1.$$

Then

$$\begin{aligned} G^{2k} = {} & X_{2k} + \left((2N-1) + q_{2k-3}^{2k-1}\right)X_{2k-2} + \left((2N-1)q_{2k-3}^{2k-1} + q_{2k-5}^{2k-1}\right)X_{2k-4} \\ & + \left((2N-1)q_{2k-5}^{2k-1} + q_{2k-7}^{2k-1}\right)X_{2k-6} + \\ & + ... + \left((2N-1)q_3^{2k-1} + q_1^{2k-1}\right)X_2 + (2N)q_1^{2k-1}e. \end{aligned}$$

i.e,

$$p^{2k}_{2k-2} = (2N-1) + q^{2k-1}_{2k-3},$$
$$p^{2k}_{2k-4} = (2N-1)q^{2k-1}_{2k-3} + q^{2k-1}_{2k-5},$$

........,

$$p^{2k}_{2} = (2N-1)q^{2k-1}_{3} + q^{2k-1}_{1}$$

and

$$p^{2k}_{0} = (2N)q^{2k-1}_{1}.$$

(2) Let

$$G^{2k} = X_{2k} + p^{2k}_{2k-2}X_{2k-2} + ... + p^{2k}_{2}X_{2} + p^{2k}_{0}e.$$

Then

$$G^{2k+1} = X_{2k+1} + \left((2N-1) + p^{2k}_{2k-2}\right) X_{2k-1} + \left((2N-1)p^{2k}_{2k-2} + p^{2k}_{2k-4}\right) X_{2k-3}$$
$$+ \left((2N-1)p^{2k}_{2k-4} + p^{2k}_{2k-6}\right) X_{2k-5} +$$
$$+ ... + \left((2N-1)p^{2k}_{4} + p^{2k}_{2}\right) X_{3} + \left((2N-1)p^{2k}_{2} + p^{2k}_{0}\right) X_{1}.$$

i.e,

$$q^{2k+1}_{2k-1} = (2N-1) + p^{2k}_{2k-2},$$
$$q^{2k+1}_{2k-3} = (2N-1)p^{2k}_{2k-2} + p^{2k}_{2k-4},$$

......,

$$q^{2k+1}_{3} = (2N-1)p^{2k}_{4} + p^{2k}_{2}$$

and

$$q^{2k+1}_{1} = (2N-1)p^{2k}_{2} + p^{2k}_{0}.$$

□

Example 1.1. *Suppose that* $N = 2$. *and let* $p^2_0 = 4$ *and* $q^3_1 = 3 + p^2_0 = 3 + 4 = 7$. *Put*

$$G^8 = X_8 + p^8_6 X_6 + p^8_4 X_4 + p^8_2 X_4 + p^8_0 e.$$

Then, by the previous proposition, we have that

$$p^8_6 = 3 + q^7_5, \quad p^8_4 = 3q^7_5 + q^7_3, \quad p^8_2 = 3q^7_3 + q^7_1 \quad \text{and} \quad p^8_0 = 4q^7_1.$$

Similarly, by the previous proposition,

$$q^7_5 = 3 + p^6_4, \quad q^7_3 = 3p^6_4 + p^6_2 \quad \text{and} \quad q^7_1 = 3p^6_2 + p^6_0,$$

$$p^6_4 = 3 + q^5_3, \quad p^6_2 = 3q^5_3 + q^5_1 \quad \text{and} \quad p^6_0 = 4q^5_1,$$

$$q^5_3 = 3 + p^4_2 \quad \text{and} \quad q^5_1 = 3p^4_2 + p^4_2,$$

$$p_2^4 = 3 + q_1^3 \qquad \textit{and} \qquad p_0^4 = 4q_1^3,$$

and

$$q_1^3 = 3 + p_0^2 = 7.$$

Therefore, combining all information,

$$G^8 = X_8 + 22\,X_6 + 202\,X_4 + 744\,X_2 + 1316\,e.$$

We have the following diagram with arrows which mean that

$$\begin{array}{ccl} \swarrow\swarrow & : & (2N-1) + [\text{former term}] \\ \searrow & : & (2N-1) \cdot [\text{former term}] \\ \swarrow & : & \cdot + [\text{former term}] \end{array}$$

and

$$\searrow\searrow \; : \quad (2N) \cdot [\text{former term}].$$

$$\begin{tikzcd}
 & & & & & & p_0^2 \arrow[d] & & = 2N \\
 & & & & & & q_1^3 \arrow[dll, shift left] \arrow[dll, shift right] \arrow[dr, shift left] \arrow[dr, shift right] & & = (2N-1) + 2N \\
 & & & & p_2^4 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr] & & & p_0^4 \arrow[dll] & \\
 & & & q_3^5 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr] & & q_1^5 \arrow[dl] \arrow[drr, shift left] \arrow[drr, shift right] & & & \\
 & & p_4^6 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr] & & p_2^6 \arrow[dl] \arrow[dr] & & & p_0^6 \arrow[dll] & \\
 & q_5^7 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr] & & q_3^7 \arrow[dl] \arrow[dr] & & q_1^7 \arrow[dl] \arrow[drr, shift left] \arrow[drr, shift right] & & & \\
 p_6^8 & & p_4^8 & & p_2^8 & & & p_0^8 & \\
 \vdots & & \vdots & & \vdots & & & \vdots &
\end{tikzcd}$$

Notation From now, we will call the above diagram the **recurrence diagram for** N. □

For examplet, when $N = 2$, we can compute p_4^6, as follows ;

$$p_0^2 = 4, \qquad q_1^3 = 7,$$

$$p_2^4 = 3 + 7 = 10, \qquad p_0^4 = 28,$$

$$q_3^5 = 3 + 10 = 13, \quad q_1^5 = 3 \cdot 10 + 28 = 58.$$

and hence $p_4^6 = 3 + 13 = 16$.

By the recurrence diagram for N, we can get that ;

Theorem 1.2. *Let $G \in (A, \tau)$ be the generating operator. Then the moment series of G is*

$$\tau\left(G^n\right) = \begin{cases} 0 & \text{if } n \text{ is odd} \\ \\ p_0^n & \text{if } n \text{ is even,} \end{cases}$$

for all $n \in \mathbb{N}$.

Proof. Assume that n is odd. Then

$$G^n = X_n + q_{n-2}^n X_{n-2} + ... + q_3^n X_3 + q_1^n X_1.$$

So, G^n does not contain the e-terms. Therefore,

$$\tau\left(G^n\right) = \tau\left(X_n + q_{n-2}^n X_{n-2} + ... + q_3^n X_3 + q_1^n X_1\right) = 0.$$

Assume that n is even. Then

$$G^n = X_n + p_{n-2}^n X_{n-2} + ... + p_2^n X_2 + p_0^n e.$$

So, we have that

$$\tau(G^n) = \tau\left(X_n + p_{n-2}^n X_{n-2} + ... + p_2^n X_2 + p_0^n e\right) = p_0^n. \blacksquare$$

Remark that the n-th moments of the generating operator in (A, τ) is totally depending on the recurrence diagram for N.

The moments of the generating operator G of $A = L(F_N)$ is well-know. But the above theorem provides the method how to get the moments of generating operator G by using the recurrence diagram.

Recall that Nica and Speicher defined the even random variable in a $*$-probability space. Let (B, τ_0) be a $*$-probability space, where $\tau_0 : B \to \mathbb{C}$ is a linear functional satisfying that $\tau_0\left(b^*\right) = \overline{\tau_0(b)}$, for all $b \in B$, and let $b \in (B, \tau_0)$ be a random variable. We say that the random variable $b \in (B, \tau_0)$ is even if it is self-adjoint and it satisfies the following moment relation ;

$$\tau_0\left(b^n\right) = 0, \text{ whenever } n \text{ is odd.}$$

By the previous theorm, the generating operator G of $A = L(F_N)$ is an even element (for all $N \in \mathbb{N}$).

Corollary 1.3. *Let* $G \in (A, \tau)$ *be the generating operator. Then* G *is even in* (A, τ). $\square$

Also, by the previous theorem, we can recompute the well-known moment series of the generating operator G of $L(F_N)$;

Corollary 1.4. *Let* $G \in (A, \tau)$ *be the generating operator. Then the operator* G *has its moment series,*

$$M_G(z) = \sum_{n=1}^{\infty} p_0^{2n} \, z^{2n} \in \Theta_1,$$

where p_0^{2n} *are the given numbers in the recurrence diagram.* $\square$

2. Operator-valued Moment Series of the Generating Operator of $L(F_2)$

Let $M_0 \subset M$ be von Neumann algebras with $1_{M_0} = 1_M$ and let $\varphi : M \rightarrow M_0$ be the conditional expectation. i.e, the surjective bimodule map φ satisfies that

$$\varphi(m_0) = m_0, \text{ for all } m_0 \in M,$$

$$\varphi(m_0 m m_0') = m_0 \cdot \varphi(m) \cdot m_0',$$

for all $m_0, m_0' \in M_0$, $m \in M$, and

$$\varphi(m^*) = \varphi(m)^*, \text{ for all } m \in M.$$

Then the algebraic pair (M, φ) is a W^*-probability space with amalgamation over M_0 (See [1]). If $m \in (M, \varphi)$, then we will call m an operator-valued or (M_0-valued) random variable.

Definition 2.1. *Let* (M, φ) *be a* W^**-probability space over* M_0 *and let* $m \in (M, \varphi)$ *be a* M_0*-valued random variable. Define the* n*-th operator-valued moment of* m *by*

$$E\left((m_1 m)(m_2 m)...(m_n m)\right),$$

for all $n \in \mathbb{N}$, *where* $m_1, ..., m_n \in M_0$ *are arbitrary. When* $m_1 = ... = m_n = 1_{M_0}$, *for all* $n \in \mathbb{N}$, *we say that the n-th operator-valued moments of* m *are trivial. i.e, the n-th* ***trivial*** M_0*-valued moments of* $m \in (M, \varphi)$ *are* $E(m^n)$, *for all* $n \in \mathbb{N}$. *We will say that the operator-valued formal series*

$$M_m^t(z) = \sum_{n=1}^{\infty} E(m^n)\, z^n \in M_0[[z]]$$

*is the t****rivial*** M_0***-valued moment series of*** $m \in (M, \varphi)$, *where* z *is the indeterminent.*

In this chapter, by using the recurrence diagram for $N = 2$, we will compute the trivial operator-valued moment series of the given generating operator

$$G = a + b + a^{-1} + b^{-1}$$

over the commutator-group von Neumann algebra $L(K)$, where $F_2 = < a, b >$ is a free group and $K = < h = aba^{-1}b^{-1} >$ is the commutator group of a and b.

First, we will define the conditional expectation $E : L(F_2) \to L(K)$ by

$$E\left(\sum_{g \in F_2} \alpha_g g\right) = \sum_{k \in K} \alpha_k k, \tag{2.1}$$

for all $\sum_{g \in F_2} \alpha_g g \in (L(F_2), E)$.

Then we can construct the W^*-probability space $(L(F_2), E)$ over its W^*-subalgebra $L(K)$. Notice that to find the conditional expectational value of the operator-valued random variable $x \in (L(F_2), E)$ is to find the h^k-terms of the operator-valued random variables x, for $k \in \mathbb{Z}$, where

$$h = aba^{-1}b^{-1} \quad \text{and} \quad h^{-1} = bab^{-1}a^{-1}.$$

First, let us provide the recurrence diagram for $N = 2$;

$$\begin{tikzcd}[column sep=small]
 & & & & & p_0^2 \arrow[d] & = 4 \\
 & & & & & q_1^3 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr, shift left] \arrow[dr, shift right] & = 7 \\
 & & & & p_2^4 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr] & & p_0^4 \arrow[dl] \\
 & & & q_3^5 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr] & & q_1^5 \arrow[dl] \arrow[dr, shift left] \arrow[dr, shift right] & \\
 & & p_4^6 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr] & & p_2^6 \arrow[dl] \arrow[dr] & & p_0^6 \arrow[dl] \\
 & q_5^7 \arrow[dl, shift left] \arrow[dl, shift right] \arrow[dr] & & q_3^7 \arrow[dl] \arrow[dr] & & q_1^7 \arrow[dl] \arrow[dr, shift left] \arrow[dr, shift right] & \\
p_6^8 & & p_4^8 & & p_2^8 & & p_0^8 \\
\vdots & & \vdots & & \vdots & & \vdots
\end{tikzcd}$$

where

$$\begin{array}{ccl} \swarrow\swarrow & : & 3+[\text{former term}] \\ \searrow & : & 3\cdot[\text{former term}] \\ \swarrow & : & \cdot+[\text{former term}] \end{array}$$

and

$$\searrow\searrow \quad : \quad 4\cdot[\text{former term}].$$

By the above recurrence diagram for $N=2$, we have that if

$$p_0^2 = 4 \qquad \text{and} \qquad q_1^3 = 3 + p_0^2 = 7,$$

and if we put $X_n = \sum_{|w|=n} w$, as the sum of all words with length n in $\{a, b, a^{-1}, b^{-1}\}$, for $n \in \mathbb{N}$, then we have the following recurrence relations (1) and (2) ;

(1) If

$$G^{2k-1} = X_{2k-1} + q_{2k-3}^{2k-1} X_{2k-3} + ... + q_3^{2k-1} X_3 + q_1^{2k-1} X_1.$$

then

$$\begin{aligned} G^{2k} = X_{2k} &+ \left(3 + q_{2k-3}^{2k-1}\right) X_{2k-2} + \left(3q_{2k-3}^{2k-1} + q_{2k-5}^{2k-1}\right) X_{2k-4} \\ &+ \left(3q_{2k-5}^{2k-1} + q_{2k-7}^{2k-1}\right) X_{2k-6} \\ &+ ... + \left(3q_3^{2k-1} + q_1^{2k-1}\right) X_2 + 4q_1^{2k-1} e. \end{aligned}$$

where

$$p_{2k-2}^{2k} = 3 + q_{2k-3}^{2k-1}, \qquad p_{2k-4}^{2k} = 3q_{2k-3}^{2k-1} + q_{2k-5}^{2k-1},$$

$$..., \, p_2^{2k} = 3q_3^{2k-1} + q_1^{2k-1} \qquad \text{and} \qquad p_0^{2k} = 4q_1^{2k-1},$$

by the recurrence diagram.

(2) If

$$G^{2k} = X_{2k} + p_{2k-2}^{2k} X_{2k-2} + ... + p_2^{2k} X_2 + p_0^{2k} e.$$

Then

$$\begin{aligned} G^{2k+1} = X_{2k+1} &+ \left(3 + p_{2k-2}^{2k}\right) X_{2k-1} + \left(3p_{2k-2}^{2k} + p_{2k-4}^{2k}\right) X_{2k-3} \\ &+ \left(3p_{2k-4}^{2k} + p_{2k-6}^{2k}\right) X_{2k-5} + \\ &+ ... + \left(3p_4^{2k} + p_2^{2k}\right) X_3 + \left(3p_2^{2k} + p_0^{2k}\right) X_1. \end{aligned}$$

where

$$q_{2k-1}^{2k+1} = 3 + p_{2k-2}^{2k}, \qquad q_{2k-3}^{2k+1} = 3p_{2k-2}^{2k} + p_{2k-4}^{2k},$$

$$..., \; q_3^{2k+1} = 3p_4^{2k} + p_2^{2k} \quad \text{and} \quad q_1^{2k+1} = 3p_2^{2k} + p_0^{2k},$$

by the recurrence diagram.

Note that h and h^{-1} are words with their length 4. Therefore, X_{4k} contains h^k-terms and h^{-k}-terms, for all $k \in \mathbb{N} \cup \{0\}$! Thus we can compute the trivial operator-valued moments of the operator G as follows ;

Theorem 2.1. *Fix $k \in \mathbb{N}$ and Let $G \in (L(F_2), E)$ be the generating operator of $L(F_2)$. Then*

(1) $E(G^k) = 0_{L(K)}$, *if k is odd.*

(2) $E\left(G^{4k}\right) = \left(h^k + h^{-k}\right) + \sum_{j=1}^{k-1} p_{4k-4j}^{4k} \left(h^{k-j} + h^{-(k-j)}\right) + p_0^{4k} h^0,$

where $p_0^4 = 28$.

(3) If $4 \nmid 2k$, in the sense that $2k$ is not a multiple by 4, then

$$E(G^{2k}) = \sum_{j=1}^{k-1} p_{(2k-2)-4j}^{2k} \left(h^{\frac{k-1}{2}-2j} + h^{-(\frac{k-1}{2}-2j)}\right) + p_0^{2k} h^0,$$

where $p_0^2 = 4$.

Proof. (1) Suppose that k is odd. Then G^k does not have the words with length $4p$, for some $p \in \mathbb{N}$, by the recurrence diagram for $N = 2$, since G^k does not have the X_{4n}-terms, for $n \in \mathbb{N}$, $4n < k$. This shows that there's no h^n-terms and h^{-n}-terms in G^k, where n is previousely given such that $2n < k$. Therefore, all odd trivial operator-valued moments of G vanish.

(2) By the straightforward computation using the recurrence diagram, we have that

$$E\left(G^{4k}\right)$$

$$= E\left(X_{4k} + p_{4k-2}^{4k}X_{4k-2} + p_{4k-4}^{4k}X_{4k-4} + ... + p_4^{4k}X_4 + p_2^{4k}X_2 + p_0^{4k}h^0\right)$$

(2.2)

$$= E(X_{4k}) + p_{4k-2}^{4k}E(X_{4k-2}) + p_{4k-4}^{4k}E(X_{4k-4}) +$$

$$... + p_4^{4k}E(X_4) + p_2^{4k}E(X_2) + p_0^{4k}h^0.$$

Since h^p and h^{-p} terms are in X_{4p}, for any $p \in \mathbb{N} \cup \{0\}$, the formular (2.2) is

(2.3)

$$E(X_{4k}) + p_{4k-4}^{4k}E(X_{4k-4}) + ... + p_4^{4k}E(X_4) + p_0^{4k}h^0$$

$$= \left(h^k + h^{-k}\right) + p_{4k-4}^{4k}(h^{k-1} + h^{-(k-1)}) + ... + p_4^{4k}(h + h^{-1}) + p_0^{4k}h^0.$$

(3) If $4 \nmid 2k$, then $k = 1, 3, 5, ...$ If $k = 1$, then we have that ;

$$E(G^2) = E\left(X_2 + 4h^0\right) = 4h^0.$$

If $k \neq 1$ is odd, then

$$E(G^{2k})$$

$$= E(X_{2k} + p_{2k-2}^{2k}X_{2k-2} + p_{2k-4}^{2k}X_{2k-4} + p_{2k-6}^{2k}X_{2k-6} +$$

$$... + p_4^{2k}X_4 + p_2^{2k}X_2 + p_0^{2k}h^0)$$

$$= E(X_{2k}) + p_{2k-2}^{2k}E(X_{2k-2}) + p_{2k-4}^{2k}E(X_{2k-4}) + p_{2k-6}^{2k}E(X_{2k-6}) +$$

$$... + p_4^{2k}E(X_4) + p_2^{2k}E(X_2) + p_0^{2k}h^0$$

$$= 0_B + p_{2k-2}^{2k}\left(h^{k-1} + h^{-(k-1)}\right) + 0_B + p_{2k-6}^{2k}\left(h^{k-3} + h^{-(k-3)}\right) +$$

$$... + p_4^{2k}(h + h^{-1}) + 0_B + p_0^{2k}h^0,$$

since X_{2k-2}, $X_{2k-6}, ..., X_4$ contain h^p-terms and h^{-p}-terms, for $p \in \mathbb{N} \cup \{0\}$. ∎

By the previous trivial operator-valued moments of the generating operator G of $L(F_2)$, we have the following result ;

Corollary 2.2. *Let $(L(F_2), E)$ be the W^*-probability spcae over $L(K)$ and let $G \in (L(F_2), E)$ be the generating operator of $L(F_2)$. Then the trivial operator-valued moment series of G is*

$$M_G(z) = \sum_{n=1}^{\infty} b_{2n}\, z^n \in L(K)[[z]],$$

where

$$b_{4n} = (h^n + h^{-n}) + \sum_{j=1}^{n-1} p_{4n-4j}^{4n} \left(h^{n-j} + h^{-(n-j)} \right) + p_0^{4n} h^0$$

and

$$b_{2k} = \sum_{j=1}^{k-1} p_{(2k-2)-4j}^{2k} \left(h^{\frac{k-1}{2}-2j} + h^{-(\frac{k-1}{2}-2j)} \right) + p_0^{2k} h^0,$$

where $4 \nmid 2k$, for all $n, k \in \mathbb{N}$. $\square$

Remark 2.1. *Suppose we have the free group factor $L(F_N)$, where $N \in \mathbb{N}$. Then we can extend the above result for the general N. i.e, we can take $F_N = < g_1, ..., g_N >$ and $K = < h >$, where*

$$k = g_1 \cdots g_N \cdot g_1^{-1} \cdots g_N^{-1}.$$

By defining the canonical conditional expectation $E : L(F_N) \rightarrow L(K)$, we can construct the W^*-probability space with amalgamation over $L(K)$. Similar to the case when $N = 2$, by using the recurrence diagram for N, we can compute the trivial operator-valued moments of the generating operator

$$G_N = g_1 + ... + g_N + g_1^{-1} + ... + g_N^{-1}.$$

When $N = 2$, to find the trivial operator-valued moments of G_2 is to find the h^k-terms of G_2^n, for $k \in \mathbb{Z}$, $n \in \mathbb{N}$. But in the general case, to find the trivial operator-valued moments of G_N is to find the k^p-terms of G_N^q, for $p \in \mathbb{Z}$, $q \in \mathbb{N}$. So, we have to choose the $X_{(2N)p}$-terms, for all $p \in \mathbb{N}$, containing $k^{\pm p}$-terms !

References

[1] R. Speicher, Combinatorial Theory of the Free Product with Amalgamation and Operator-Valued Free Probability Theory, AMS Mem, Vol 132 , Num 627 , (1998).

[2] A. Nica, R-transform in Free Probability, IHP course note.

[3] R. Speicher, Combinatorics of Free Probability Theory IHP course note.

[4] A. Nica, D. Shlyakhtenko and R. Speicher, R-cyclic Families of Matrices in Free Probability, J. of Funct Anal, 188 (2002), 227-271.

[5] A. Nica and R. Speicher, R-diagonal Pair-A Common Approach to Haar Unitaries and Circular Elements, (1995), Preprint.

[6] D. Shlyakhtenko, Some Applications of Freeness with Amalgamation, J. Reine Angew. Math, 500 (1998), 191-212.

[7] A. Nica, D. Shlyakhtenko and R. Speicher, R-diagonal Elements and Freeness with Amalgamation, Canad. J. Math. Vol 53, Num 2, (2001) 355-381.

[8] A. Nica, R-transforms of Free Joint Distributions and Non-crossing Partitions, J. of Func. Anal, 135 (1996), 271-296.

[9] D.Voiculescu, K. Dykemma and A. Nica, Free Random Variables, CRM Monograph Series Vol 1 (1992).

[10] D. Voiculescu, Operations on Certain Non-commuting Operator-Valued Random Variables, Astérisque, 232 (1995), 243-275.

[11] D. Shlyakhtenko, A-Valued Semicircular Systems, J. of Funct Anal, 166 (1999), 1-47.

[12] I. Cho, The Moment Series and The R-transform of the Generating Operator of $L(F_N)$, (2003), Preprint.

[13] I. Cho, The Moment Series of the Generating Operator of $L(F_2) *_{L(K)} L(F_2)$, (2003), Preprint

[14] I. Cho, An Example of Moment Series under the Compatibility, (2003), Preprint

[15] F. Radulescu, Singularity of the Radial Subalgebra of $L(F_N)$ and the Pukánszky Invariant, Pacific J. of Math, vol. 151, No 2 (1991), 297-306.

Dep. of Math, Univ. of Iowa, Iowa City, IA, U. S. A
E-mail address: `ilcho@math.uiowa.edu`